



Application  
Parameters

Duct

Point Measurement

Output Signal / Measuring range (differential Pressure):

Switch / 20...300 Pa	<b>01APS-10R</b>	
Switch / 50...500 Pa	<b>01APS-10U</b>	
Switch / 200...1000 Pa	<b>01APS-101</b>	
Switch / 500...2500 Pa	<b>01APS-104</b>	

With LCD-Display:

DC 0...5 V, DC 0...10 V	<b>22ADP-154</b>		DC 0...5 V, DC 0...10 V	<b>22ADP-154L</b>	
DC 0...5 V, DC 0...10 V	<b>22ADP-156</b>		DC 0...5 V, DC 0...10 V	<b>22ADP-156L</b>	
DC 0...5 V, DC 0...10 V	<b>22ADP-15Q</b>		DC 0...5 V, DC 0...10 V	<b>22ADP-15QB</b>	
DC 0...5 V, DC 0...10 V	<b>22ADP-15QA</b>		DC 0...5 V, DC 0...10 V	<b>22ADP-15QL</b>	

DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-184</b>		DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-184L</b>	
DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-186</b>		DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-186L</b>	
DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-18Q</b>		DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-18QB*</b>	
DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-18QA*</b>		DC 0...5 V, DC 0...10 V 4...20 mA	<b>22ADP-18QL</b>	

\*Auto-Zero